



Description: Adaptor, BNC female – IEC male Push On.

DATA SHEET

Electrical

	Specification		Standard
Frequency Range	5 MHz – 3.000 MHz		
Impedance	75 Ω nominal		
	Better Than	Measured – Worst case of 5 measurements	
Return Loss Gated	24 dB	≥ 27.2 dB	5 MHz – 500 MHz
	24 dB	≥ 27.2 dB	500 MHz – 860 MHz
	23 dB	≥ 26.1 dB	860 MHz – 1.000 MHz
	21 dB	≥ 24.0 dB	1.000 MHz – 1.750 MHz
	19 dB	≥ 22.8 dB	1.750 MHz – 2.150 MHz
	17 dB	≥ 20.2 dB	2.150 MHz – 3.000 MHz
Insertion Loss	0.13 dB	≤ 0.1 dB	5 MHz – 3.000 MHz
Shielding Effectiveness (Measured with CoMeT)	Transfer Impedance @ 5 – 30 MHz		≤ 0.25 m Ω /item
	Screening Attenuation @ 30 – 1.000 MHz		≥ 115.7 dB
	Screening Attenuation @ 1.000 – 2.000 MHz		≥ 120.4 dB
	Screening Attenuation @ 2.000 – 3.000 MHz		≥ 121.1 dB
Common Path Distortion	≤ -110 dBc		ANSI/SCTE 109 2005
Amp. Rating	≤ 8 A @ 60 V.		
Dielectric Strength	≥ 3 kV.		IEC 61169-1
Insulation Resistance	≥ 29.99 G Ω @ 500 V.		IEC 61169-1

Environmental

	Specification	Standard
Temperature range Operating	-40°C to +60°C	
Temperature range Installation	-5°C to +50°C	
Corrosion Protection		ASTM B 117-94

Mechanical

	Specification	Standard
Interface	BNC female IEC male	IEC 61169-8 IEC 61169-2

Material and Finish

	Specification	Standard
Housing	NiSn (NITIN) plated Brass	ASTM B605
Inner conductor	NiSn (NITIN) plated Brass	ASTM B605
Insulator	PEHD	

In order to continue to supply the best products, PPC reserves the right to change the products and specifications at any time without prior notice.

Measurement setup:

Nm-BNCm, **BNCFIECM-PUSHON**, 58m-IECf, Nm-58f

All results are the worst case result of measurement of 5 adaptors.

All tests are performed using instruments calibrated in accordance to our ISO 9001 certification.

Return Loss, Insertion Loss and Shielding are measured with Rohde & Schwarz ZNB8 Network Analyzer, according to IEC standards.

CPD (Common Path Distortion) are measured with hp Spectrum Analyzer hp 8591E, according to SCTE standard.

In case of over current (≥ 8 A.) there is a risk for high temperature inside the adaptor, which can cause damage of the insulator.

Further test reports, technical specifications and installation instructions can be obtained on request.