



Connector XReference Chart Rev 05-04-10

Brand	Cable Size	Cable Type	Connector Part#	Prep Tool	Coring Bit	Guide Pin
RFS	1/2"	SCF12	CC-XXX-SCF12	SP-1/2-UNIV - Hand tool	1**	N/A
	1/2"	SCF12	CC-XXX-SCF12	SP-1/2-UNIVD - Drill Tool	2	N/A
	1/2"	LCF12	CC-XXX-L4	SP-1/2-LDF4 or SP-1/2-LDF4D	1	N/A
	7/8"	LCF78 (Rev J or Older)	CC-XXX-L5	SP-78	2***	B***
	7/8"	LCF78 (Rev JA)	CC-XX-JA5	SP-78	2***	A***
	1 1/4"	UCF114	CC-XX-U6	SP-114	2	C
	1 5/8"	LCF158 (Rev J and Older)	CC-XX-L7	SP-158	1	B *
	1 5/8"	LCF158 (Rev JA)	CC-XX-JA7	SP-158	1	A *
Andrew	1/2"	FSJ4	CC-XXX-F4	SP-1/2-UNIV - Hand tool	1 **	N/A
	1/2"	FSJ4	CC-XXX-F4	SP-1/2-UNIVD - Drill Tool	1	N/A
	1/2"	LDF4 HL4RP	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	1	N/A
	7/8"	AVA5 AL5	CC-XX-A5	SP-78	1***	A***
	7/8"	LDF5	CC-XX-L5	SP-78	2***	B***
	7/8"	VXL5	CC-XX-V5	SP-78	2***	C***
	1 1/4"	AVA 6 AL6	CC-XX-A6	SP-114	1	A
	1 1/4"	LDF6	CC-XX-L6	SP-114	2	B
	1 5/8"	AVA7 AL7	CC-XX-A7	SP-158	1	A *
	1 5/8"	LDF7	CC-XX-L7	SP-158	1	B *
1 5/8"	VXL7	CC-XX-V7	SP-158	1	C	
CommScope	1/2"	SFX500	CC-XXX-S4	SP-500	N/A	N/A
	1/2"	CR540 FXL540	CC-XXX-540	SP-540	N/A	N/A
	7/8"	FXL780 CR780	CC-XX-780	SP-780	N/A	N/A
	1 5/8"	FXL1873 CR1873	CC-XX-1873	SP-1873	N/A	N/A
NK Draka	1/2"	RFF1200	CC-XXX-RFF4	SP-1/2-UNIV - Hand tool	3	N/A
	1/2"	RFF1200	CC-XXX-RFF4	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	RFA1200	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	2	N/A
	7/8"	RFA78	CC-XX-RFA5	SP-78	2***	A***
	1 1/4"	RFA114	CC-XX-RFA6	SP-114	1	B
	1 5/8"	RFA158	CC-XX-RFA7	SP-158	1	C
Eupen	1/2"	EC4HF	CC-XXX-EC4HF	SP-1/2-UNIV Hand Tool	1**	N/A
	1/2"	EC4HF	CC-XXX-EC4HF	SP-1/2-UNIVD - Drill Tool	1	N/A
	1/2"	EC4	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	2	N/A
	7/8"	EC5	CC-XX-EC5	SP-78	1***	A***
	1 1/4"	EC6	CC-XX-EC6	SP-114	1	A
	1 5/8"	EC7	CC-XX-EC7	SP-158	1	A *
Leoni	1/2"	Flexline 1/2"S	CC-XXX-FL4S	SP-1/2-UNIV - Hand tool	3	N/A
	1/2"	Flexline 1/2"S	CC-XXX-FL4S	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	Flexline 1/2"R	CC-XXX-L4	SP-1/2-LDF4 or SP-1/2-LDF4D	2	N/A
	7/8"	Flexline 7/8"R	CC-XX-FL5	SP-78	1	A***
	1 1/4"	Flexline 1-1/4"R	CC-XX-FL6	SP-114	1	B
	1 5/8"	Flexline 1-5/8"R	CC-XX-FL7	SP-158	2	B*
LS Cable	1/2"	HFSC 12D	CC-XXX-HF4	SP-1/2-UNIV - Hand tool	2	N/A
	1/2"	HFSC 12D	CC-XXX-HF4	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	LHF 12D	CC-XXX-LH4	SP-1/2-LH4D	LS	N/A
	7/8"	LHF 22D	CC-XX-LH5	SP-78	1	A***
	1 1/4"	LHF 33D	CC-XX-LH6	SP-114	1	B
	1 5/8"	LHF 42D	CC-XX-LH7	SP-158	2	A*

<p>Interface Key: XX/XXX =</p>	<p>DM = Din Male DF = Din Female NM = N Male NF = N Female DRA = Din Male Right Angle NRA = N Male Right Angle</p>	<p>* Early SP-158 Tool: A = Unmarked Pin B = Pin Marked "LDF"</p> <p>** Early SP-1/2-UNIV Tool: 1 = Unmarked Coring Bit</p>	<p>*** Early SP-78 Tool: Coring Bits 1 = AL / AVA or RFS 2 = LDF or VXL Guide Pins A = AL / AVA or RFS B = LDF C = VXL</p>	<p>For Customer Service Call: 315-431-7200 or 800-800-6652</p> <p>24 Hour Technical Assistance: 888-201-6073</p>
------------------------------------	--	---	--	--