



**Connector XReference Chart** Rev 06-22-2011

Brand	Cable Size	Cable Type	Connector Part#	Prep Tool	Coring Bit	Guide Pin
<b>RFS</b>	1/2"	SCF12	CC-XXX-SCF12	SP-1/2-UNIV - Hand tool	1**	N/A
	1/2"	SCF12	CC-XXX-SCF12	SP-1/2-UNIVD - Drill Tool	2	N/A
	1/2"	LCF12	CC-XXX-L12	SP-1/2-LDF4 or SP-1/2-LDF4D	1	N/A
	7/8"	LCF78 (Rev J or Older)	CC-XXX-L5	SP-78	2***	B***
	7/8"	LCF78 (Rev JA)	CC-XX-JA5	SP-78	2***	A***
	1 1/4"	UCF114	CC-XX-U6	SP-114	2	C
	1 5/8"	LCF158 (Rev J and Older)	CC-XX-L7	SP-158	1	B *
	1 5/8"	LCF158 (Rev JA)	CC-XX-JA7	SP-158	1	A *
<b>Andrew</b>	1/2"	FSJ4	CC-XXX-F4	SP-1/2-UNIV - Hand tool	1 **	N/A
	1/2"	FSJ4	CC-XXX-F4	SP-1/2-UNIVD - Drill Tool	1	N/A
	1/2"	LDF4 HL4RP	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	1	N/A
	7/8"	AVA5 AL5	CC-XX-A5	SP-78	1***	A***
	7/8"	LDF5	CC-XX-L5	SP-78	2***	B***
	7/8"	VXL5	CC-XX-V5	SP-78	2***	C***
	1 1/4"	AVA 6 AL6	CC-XX-A6	SP-114	1	A
	1 1/4"	LDF6	CC-XX-L6	SP-114	2	B
	1 5/8"	AVA7 AL7	CC-XX-A7	SP-158	1	A *
	1 5/8"	LDF7	CC-XX-L7	SP-158	1	B *
1 5/8"	VXL7	CC-XX-V7	SP-158	1	C	
<b>CommScope</b>	1/2"	SFX500	CC-XXX-S4	SP-500	N/A	N/A
	1/2"	CR540 FXL540	CC-XXX-540	SP-540	N/A	N/A
	7/8"	FXL780 CR780	CC-XX-780	SP-780	N/A	N/A
	1 5/8"	FXL1873 CR1873	CC-XX-1873	SP-1873	N/A	N/A
<b>NK Draka</b>	1/2"	RFF1200	CC-XXX-RFF4	SP-1/2-UNIV - Hand tool	3	N/A
	1/2"	RFF1200	CC-XXX-RFF4	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	RFA1200	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	2	N/A
	7/8"	RFA78	CC-XX-RFA5	SP-78	2***	A***
	1 1/4"	RFA114	CC-XX-RFA6	SP-114	1	B
	1 5/8"	RFA158	CC-XX-RFA7	SP-158	1	C
<b>Eupen</b>	1/2"	EC4HF	CC-XXX-EC4HF	SP-1/2-UNIV Hand Tool	1**	N/A
	1/2"	EC4HF	CC-XXX-EC4HF	SP-1/2-UNIVD - Drill Tool	1	N/A
	1/2"	EC4	CC-XXX-L4	SP-1/2-LDF4 or SP-12-LDF4D	2	N/A
	7/8"	EC5	CC-XX-EC5	SP-78	1***	A***
	1 1/4"	EC6	CC-XX-EC6	SP-114	1	A
	1 5/8"	EC7	CC-XX-EC7	SP-158	1	A *
<b>Leoni</b>	1/2"	Flexline 1/2"S	CC-XXX-FL4S	SP-1/2-UNIV - Hand tool	3	N/A
	1/2"	Flexline 1/2"S	CC-XXX-FL4S	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	Flexline 1/2"R	CC-XXX-L4	SP-1/2-LDF4 or SP-1/2-LDF4D	2	N/A
	7/8"	Flexline 7/8"R	CC-XX-FL5	SP-78	1	A***
	1 1/4"	Flexline 1-1/4"R	CC-XX-FL6	SP-114	1	B
	1 5/8"	Flexline 1-5/8"R	CC-XX-FL7	SP-158	2	B*
<b>LS Cable</b>	1/2"	HFSC 12D	CC-XXX-HF4	SP-1/2-UNIV - Hand tool	2	N/A
	1/2"	HFSC 12D	CC-XXX-HF4	SP-1/2-UNIVD - Drill Tool	3	N/A
	1/2"	LHF 12D	CC-XXX-LH4	SP-1/2-LH4D	LS	N/A
	7/8"	LHF 22D	CC-XX-LH5	SP-78	1	A***
	1 1/4"	LHF 33D	CC-XX-LH6	SP-114	1	B
	1 5/8"	LHF 42D	CC-XX-LH7	SP-158	2	A*

Interface Key:  
XX/XXX =  
DM = Din Male  
DF = Din Female  
NM = N Male  
NF = N Female  
DRA = Din Male Right Angle  
NRA = N Male Right Angle

\* Early SP-158 Tool:  
A = Unmarked Pin  
B = Pin Marked "LDF"  
  
\*\* Early SP-1/2-UNIV Tool:  
1 = Unmarked Coring Bit

\*\*\* Early SP-78 Tool:  
Coring Bits  
1 = AL / AVA or RFS  
2 = LDF or VXL  
Guide Pins  
A = AL / AVA or RFS  
B = LDF  
C = VXL

**For Customer Service Call:**  
315-431-7200 or 800-800-6652  
  
**24 Hour Technical Assistance:**  
888-201-6073